

Specifications

Roland JUPITER-80: Synthesizer

Keyboard	76 keys (with velocity and channel aftertouch)
Sound Generator Section	
Maximum Polyphony	256 voices (varies according to the sound generator load)
Parts	4 parts (Upper, Lower, Solo, Percussion)
Tones	Registrations: 256 Live Sets: 2,560
Effects	for Live Set (Upper/Lower Part) <ul style="list-style-type: none"> Multi-Effects (MFX): 4 units (parallel connection only), 76 types per each Upper/Lower (total: 8 units) Reverb: 1 unit, 5 types per each Upper/Lower (total: 2 units)
	for Solo Part/Percussion Part <ul style="list-style-type: none"> Compressor + Equalizer + Delay: 1 set per each Solo/Percussion (total: 2 sets) Reverb: 1 unit, 5 types
	Master Effects <ul style="list-style-type: none"> 4-Band Equalizer: 1 unit
USB Memory Song Player/Recorder Section	
Tracks	1 stereo track
Playable File Format	Audio File: WAV, AIFF, MP3
Recording File Format	Audio File: WAV (44.1 kHz, 16-bit Linear, stereo)
Effects	4-Band Equalizer: 1 unit
External Memory	USB Flash Memory (sold separately) * Use USB Flash Memory sold by Roland. We cannot guarantee operation if other products are used.

Others	
Arpeggiator	Preset: 128 styles User: 128 styles
Harmony Intelligence	17 types
Controllers	D Beam Controller Pitch Bend/Modulation Lever Assignable buttons ([S1], [S2]) Assignable knobs ([E1]–[E4]) PART LEVEL sliders (PERC, LOWER, UPPER, SOLO)
Display	Graphic Color LCD 800 x 480 dots (touch screen)
Connectors	PHONES jack (stereo 1/4-inch phone type) MAIN OUT jacks (L, R) (XLR type) MAIN OUT jacks (L/MONO, R) (1/4-inch TRS phone type) SUB OUT jacks (L, R) (1/4-inch phone type) AUDIO IN jack (Stereo miniature phone type) DIGITAL AUDIO OUT jack (COAXIAL) FOOT PEDAL jacks (CTRL 1, CTRL 2, HOLD) MIDI Connectors (IN, OUT, THRU) USB COMPUTER port (Audio/MIDI) USB Memory port AC IN jack
Power Consumption	25 W
Dimensions	1,230.9 (W) x 439.3 (D) x 139.6 (H) mm 48-1/2 (W) x 17-5/16 (D) x 5-1/2 (H) inches
Weight	17.7 kg 39 lbs 1 oz
Accessories	Owner's manual CD-ROM (USB Audio/MIDI driver) DVD-ROM (SONAR LE) USB MEMORY Protector Power Cord
Options (sold separately)	Keyboard stand: KS-J8, KS-G8, KS-18Z (When using the KS-18Z, ensure that the height of the unit is one meter or lower.) Pedal switch: DP series Footswitch: BOSS FS-5U Expression pedal: EV-5 Stereo Headphones USB Flash Memory

* In the interest of product improvement, the specifications and/or appearance of this unit are subject to change without prior notice.